

## SDS6000A Typical Noise Floor

June 24, 2022

Here are the typically expected noise floor numbers for the SDS6000A Oscilloscope:

### Vertical Scale Noise Floor (rms@50 ohms)

0.5 mV/div	135 uV
1 mV/div	135 uV
2 mV/div	136 uV
5 mV/div	200 uV
10 mV/div	325 uV
20 mV/div	490 uV
50 mV/div	1.10 mV
100 mV/div	2.01 mV
200 mV/div	5.10 mV
500 mV/div	11.60 mV
1 V/div	20.95 mV

Note: Uses StdDev measurement @ 5 GSa/s, 10 MPts/ch



### **North American Headquarters**

SIGLENT Technologies America, Inc  
6557 Cochran Rd Solon, Ohio 44139  
Tel: 440-398-5800  
Toll Free: 877-515-5551  
Fax: 440-399-1211  
[info@siglent.com](mailto:info@siglent.com)  
[www.siglentamerica.com/](http://www.siglentamerica.com/)

### **European Sales Offices**

SIGLENT TECHNOLOGIES EUROPE GmbH  
Staetzlinger Str. 70  
86165 Augsburg, Germany  
Tel: +49(0)-821-666 0 111 0  
Fax: +49(0)-821-666 0 111 22  
[info-eu@siglent.com](mailto:info-eu@siglent.com)  
[www.siglenteu.com](http://www.siglenteu.com)

### **Asian Headquarters**

SIGLENT TECHNOLOGIES CO., LTD.  
Blog No.4 & No.5, Antongda Industrial Zone,  
3rd Liuxian Road, Bao'an District,  
Shenzhen, 518101, China.  
Tel: + 86 755 3661 5186  
Fax: + 86 755 3359 1582  
[sales@siglent.com](mailto:sales@siglent.com)  
[www.siglent.com/ens](http://www.siglent.com/ens)